

The following system parameters can be set from user perspective:

- system date and time
- time of lock release
- time frame for closing all safe-boxes
- time between card checking and PIN entering
- number of possible failed attempts to enter the PIN
- time of card blocking after the possible number of failed attempts to set the PIN has been exceeded
- warning time (before alarm is triggered off)
- a code for emergency opening of all safe-boxes

Options in addition to the standard module:

- PC communication module enabling a serial transmission in RS 232 or RS 485 protocol
- programme modification or upgrade according to user requirements
- real-time display of actual status on PC



BASIC PARAMETERS

Number of drawers

- base module UK 20 - 20
- optional module UK 30 - 30

Number of safe-boxes per one set

- basic: 1 x UK 20 (20 schránek)
- optional: 1 x UK 20 + 1 x UK 30 (50 schránek)
1 x UK 20 + 2 x UK 30 (80 schránek)

Number of sets

- 100 at most

Number of users

- 250 per one set

Needed for opening

- user card and PIN (PIN optional)

Signalling

- sound signal, display, flashing diode on each safe-box, relay alarm output

Record of operation history

- off-line – 5000 entries at most
- on-line – no limitation

Power supply

- 230 V \pm 15 V

Humidity of air

- 50–90 % without condensation

Dimensions (w/h/d), weight

- 560/610/280 mm (both types)
- UK 20 – 58 kg
- UK 30 – 62 kg

Assembly

- affixing to the wall

OTHERS

Depository software application can be adjusted according to the client's wish. Depository colour can also be altered according to the client's wish.

CERTIFICATION

ISO 9002, National Security Office (NBÚ), Czech STD, Depository - attestation, Military Technical Institute of Electronics

CONTACTS

Kolín, Czech Republic

Plynářská 671
280 02 Kolín IV., CZ
tel.: +420 321 727 893
fax: +420 321 720 581

Praha, Czech republic

Cimburkova 23
130 00 Praha 3, CZ
tel.: +420 222 782 376
tel./fax: +420 222 782 809

www.raisa.cz

e-mail: info@raisa.cz